

Tastaturi Camere NV-KBD40



Caracteristici

- tastatura fabricata pentru speed dome-urile NOVUS® comandate de la distanta, alte camere NOVUS® care au incorporata interfata RS-485
- Protocoale pentru controlul camerelor speed domes si alte camere tip: Novus-C, Novus-C1, Novus-C2, Pelco-D
- joystick cu 3 axe si cu inel de control al zoom-ului
- 33 taste multifunctionale
- 2 nivele de acces: administrator (acces protejat prin parola) si operator
- afisaj 2 x 16 digiti
- Alimentare: 9 VDC

Specificatii	Description
Conectarea echipamentului	Camere PTZ: NOVUS® CAMA-I, NOVUS® CAMA-II Series speed domes, NOVUS® CAMA-mini Other NOVUS® cameras: NVC-625DN, NVC-660DN, NVC-825DN, NVC-860DN, NVC-HDN520ZL, NVC-HDN370HZL-2 All-In-One (pana la 30 de camere cu viteze diferite)
Protocol Camera	Novus-C, Novus-C1, Novus-C2, Pelco-D
Joystick	Joystick cu 3 axe (auto-returning, zoom)
Butoane	33 de taste multifunctionale
Afisaj	16 x 2 backlit LCD
Port-uri externe	1 x RS-485 (2 x RJ-11) pentru conectarea cu camere PTZ
Alimentare	9 VDC
Consum	3 W
Temperatura de lucru	5°C ~ 40°C
Dimensiuni (mm)	335 (W) x 56 (H) x 180 (D)
Greutate	1.25 kg